

Signal Processing

Precision interpolator / splitter, precision sine multiplier

Converting of SinCos encoder signals into multiplied

SinCos output signals and HTL or TTL output signals

HEAG 160



HEAG 160

Features

- Converting of SinCos signals into multiplied SinCos signals
- Additional interpolation of HTL or TTL signals (multiplying or dividing)
- Oversampling with 24 MHz
- Digitally pre-filter
- Very high output frequency possible

Optional

- Internal pre-amplifier
- Two sine inputs for compensating radial runout of the connected encoder
- Error output, external voltage supply

Technical data - electrical ratings

Voltage supply	5 VDC \pm 5 % 10...30 VDC
Consumption	\leq 500 mA (5 VDC) \leq 300 mA (10...30 VDC)
Inputs	SinCos 2x SinCos
Input signals	A+, A-, B+, B-, R+, R-
Input frequency	\leq 0 kHz
Outputs	SinCos + TTL SinCos + HTL Error output
Output signals	A+, B+, R+, A-, B-, R- Option: A+, B+, R+, A-, B-, R-, Error-
Output frequency	\leq 2 MHz (HTL) \leq 5 MHz (TTL) \leq 600 kHz (SinCos)
Amplitude resolution	12 bit
Interpolation factor for SinCos output (multiplying)	1...128
Interpolation factor for HTL output (multiplying)	1...2048
Interpolation factor for HTL output (dividing)	1/2...1/2048
Interpolation factor for TTL output (multiplying)	1...2048
Interpolation factor for TTL output (dividing)	1/2...1/2048

Technical data - mechanical design

Dimensions W x H x L	122 x 122 x 80 mm
Protection DIN EN 60529	IP 65
Operating temperature	0...+50 °C
Resistance	DIN EN 60068-2-6 Vibration 1 g, 50-2000 Hz DIN EN 60068-2-27 Shock 30 g, 11 ms
Weight approx.	1 kg
Connection	Connector M23, 12-pin Connector, 3-pin, external voltage supply

Signal Processing


Precision interpolator / splitter, precision sine multiplier

Converting of SinCos encoder signals into multiplied SinCos output signals and HTL or TTL output signals

HEAG 160

Part number

HEAG 160 - - - - - - - - - -



Interpolation factor for SinCos output

1	4	16	64
2	8	32	128

Interpolation factor for HTL/TTL output

1	32	1024	1/16	1/512
2	64	2048	1/32	1/1024
4	128	1/2	1/64	1/2048
8	256	1/4	1/128	
16	512	1/8	1/256	

Signal Processing

Precision interpolator / splitter, precision sine multiplier

Converting of SinCos encoder signals into multiplied SinCos output signals and HTL or TTL output signals


HEAG 160

Terminal assignment

View A - Input encoder signals

Flange socket, female contacts, counter-clockwise


Female	Assignment
Pin 1	B- (inv.)
Pin 2	5 VDC
Pin 3	R+ (zero pulse)
Pin 4	R- (zero pulse inv.)
Pin 5	A+
Pin 6	A- (inv.)
Pin 7	n.c.
Pin 8	B+
Pin 9	n.c.
Pin 10	0 V
Pin 11	0 V
Pin 12	5 VDC



View C - TTL or HTL output

Flange socket, male contacts, counter-clockwise


Male	Assignment
Pin 1	B- _{TTL or HTL} (inv.)
Pin 2	n.c.
Pin 3	R+ _{TTL or HTL} (zero pulse)
Pin 4	R- _{TTL or HTL} (zero pulse inv.)
Pin 5	A+ _{TTL or HTL}
Pin 6	A- _{TTL or HTL} (inv.)
Pin 7	n.c.
Pin 8	B+ _{TTL or HTL}
Pin 9	n.c.
Pin 10	0 V
Pin 11	0 V
Pin 12	n.c.



View B - sin/cos output

Flange socket, male contacts, counter-clockwise

Male	Assignment
Pin 1	B- _{MULT} (inv.)
Pin 2	5 VDC (n.c. at option with external voltage supply)
Pin 3	R+ _{MULT} (zero pulse)
Pin 4	R- _{MULT} (zero pulse inv.)
Pin 5	A+ _{MULT}
Pin 6	A- _{MULT} (inv.)
Pin 7	n.c. (Error- at option with error output)
Pin 8	B+ _{MULT}
Pin 9	n.c.
Pin 10	0 V
Pin 11	0 V
Pin 12	5 VDC (n.c. at option with external voltage supply)



View D - External power supply

Male contacts

Male	Assignment
Pin 1	10 ... 30 VDC
Pin 3	0 V
Pin 4	Shield



