

# **IPF** ELECTRONIC

### DT98C785

### PRESSURE SENSORS • CONNECTION G1/8" OUTER THREAD

Pressure sensors are suitable for measuring different media with high accuracy. They are available with switching output and/or analog output. Using PC software, the measured values can be recorded depending on the device type. These sensors can be used in all areas of e.g. pneumatic and hydraulic applications.



### **MECHANICAL DATA**

Ambient temperature	-20 °C 80 °C
Bursting pressure	42 bar
Degree of protection (IP)	IP67
Explosion-proof	No
For gaseous media	Yes
For liquid media	Yes
Front-flush membrane	Yes
Housing design	Cylinder plain
Housing material	Chromium-nickel steel
Max. operating pressure	20000 hPa
Max. operating pressure	20 bar
Medium temperature	-30 °C 100 °C
Nominal pressure	10 bar
Pressure transmitter	Yes
Sensing element material	Chromium-nickel steel
Sensor diameter	27 mm
Sensor length	53 mm
Thread length	20.5 mm
Thread pitch	1.81 mm
Type of pressure connection	G1/2 inch B
With hand operation	No

### **ELECTRICAL DATA**

Electronic version	Yes
End value measuring range, pressure	1000000 Pa
Initial value of measuring range, pressure	0 Pa
IO-Link compatible	No
Measurement method	Relative
Measuring range pressure (MAX)	10 bar
Number of pins	2
Operating voltage	10 V 30 V

# **IPF** ELECTRONIC

ELECTRICAL DATA	
Rated operating voltage Ue at DC	10 V 30 V
Relative linearity deviation	0.5 %
Relative measurement accuracy	0.3 %
Relative repeat accuracy	0.2 %
Response time	10 ms
Reverse polarity protection	Yes
Short-circuit-proof	Yes
Cuitable as 2 maint as stual	N.L.

Short-circuit-proof	163
Suitable as 2-point control	No
Suitable as limiter	No
Suitable as monitor	No
Temperature drift	0.2 %
Type of analog output	4 mA 20 mA
Type of electrical connection	Plug-in connection M12
Voltage type	DC
With manual on/off switch	No

### **OTHER DATA**

For hydraulic applications	Yes
For pneumatic applications	Yes
Measuring display	Relative

## DIMENSIONAL DRAWING

### INSTALLATION



Mounting / Installation may only be carried out by a qualified electrician!





### **SAFETY WARNINGS**

Before initial operation, please make sure to follow all safety instructions that may be provided in the product information!