

NG780201

POWER SUPPLY UNITS • SWITCHING POWER SUPPLIES 230V AC

Pulsed power supplies are used to supply electrical systems or system parts with a stabilized DC voltage. Due to the lower copper losses, pulsed power supplies in the lower power range are considerably more efficient than power transformers. Furthermore, they are more compact and are lighter weight than conventional, linear regulated power supplies, which contain a heavy transformer with iron core and cause additional losses in the linear regulator.



MECHANICAL DATA

| Ambient temperature | -10 °C 50 °C |
|----------------------------------|--------------|
| Degree of protection (IP) | IP20 |
| Depth | 67 mm |
| Direct mounting possible | Yes |
| Height | 93 mm |
| Housing material | Plastic |
| Rail mounting possible | Yes |
| Storage temperature | 85 °C |
| Storage temperature | -20 °C |
| Suitable for serial installation | Yes |
| Wall mounting possible | No |
| Weight | 400 g |
| Width | 78 mm |
| | |

ELECTRICAL DATA

| | Yes |
|----------------------------------|-----------------------------------|
| 1. output voltage | 21.6 V 26.4 V |
| Frequency | 47 Hz 63 Hz |
| Max. input current | 0.96 A |
| Max. output current 1 | 2 A |
| Output voltage | 24 V |
| Output voltage, regulated | Yes |
| Overload protection | 105 150% of the power consumption |
| Power output | 48 W |
| Rated supply voltage at AC 50 Hz | 85 V 264 V |
| Rated supply voltage at DC | 120 V 370 V |
| Residual ripple | 1 % |
| Secondary voltage, adjustable | Yes |
| Suitable for safety functions | No |
| Type of electrical connection | Screw connection |
| Voltage type of supply voltage | AC/DC |


ipf electronic gmbh • Kalver Straße 25 - 27 • 58515 Lüdenscheid - Germany | Tel +49 2351 9365-0 • Fax +49 2351 9365-19 | info@ipf-electronic.com • www.ipf-electronic.com



ELECTRICAL DATA

| With LED display | Yes |
|------------------|------|
| OTHER DATA | |
| Air humidity | 90 % |
| Air humidity | 20 % |
| Stabilized | Yes |

DIMENSIONAL DRAWING



INSTALLATION





Mounting / Installation may only be carried out by a qualified electrician!



SAFETY WARNINGS

Before initial operation, please make sure to follow all safety instructions that may be provided in the product information!