

PT70C937

LASER SENSORS • DIFFUSE REFLECTION SENSORS WITH BACKGROUND SUPPRESSION

Optical sensors function contactlessly. They detect objects independent of their characteristics (e.g., shape, color, surface structure, material). The basic operating principle is based on the transmission and reception of light. There are three different versions: 1. The through-beam sensor consists of two separate devices, a transmitter and a receiver that are aligned with one another. If the light beam between the two devices is interrupted, the switching output integrated in the receiver changes its status. 2. With the retro-reflective sensor, the transmitter and receiver are located in one device. The emitted light beam is reflected back to the receiver by a reflector that is to be mounted opposite the device. As soon as the light beam is interrupted, the switching output integrated in the device changes its status. 3. With the diffuse reflection sensor, the transmitter and receiver are in one device. The emitted light beam is reflected by the object that is to be detected. As soon as the receiver detects the reflected light, the switching output integrated in the device changes its status.



MECHANICAL DATA

Ambient temperature	-40 °C ... 50 °C
Degree of protection (IP)	IP67
Housing design	Cuboid
Housing material	Zinc die-cast
Material of optical surface	Glass
Reflector included in the scope of delivery	No
Sensor height	90 mm
Sensor length	70 mm
Sensor width	30 mm
Storage temperature	70 °C
Storage temperature	-35 °C

ELECTRICAL DATA

Adjustment range	100 mm ... 30000 mm
Analogue output 0 mA ... 20 mA	No
Analogue output 0 V ... 10 V	No
Analogue output -10 V ... +10 V	No
Analogue output 4 mA ... 20 mA	No
IO-Link compatible	No
Max. output current	100 mA
Max. switching distance	30000 mm
No-load current	120 mA
Number of pins	5
Number of switching outputs	2
Operating voltage	18 V ... 30 V
Rated switching distance	30000 mm
Readiness delay	200 ms

ELECTRICAL DATA

Residual ripple	15 %
Response time	5 ms
Scanning function	Light-/dark-on mode
Sensing range	100 mm ... 30000 mm
Setting procedure	Teach-In
Switching frequency	100 Hz
Type of electrical connection	Connector M12
Type of switching function	Push-pull
Type of switching output	PNP/NPN
Voltage drop	1.8 V
Voltage type	DC
With LED display	Yes
With other analog output	No

OPTICAL DATA

Background suppression	Yes
Laser class	2
Laser focus distance	5000 mm
Light beam form	Point
Light source	Laser diode, red light
Light spot	28.26 mm ²
Resolution	5 mm
Triangulation	Background suppression
Wavelength of the sensor	658 nm

DIMENSIONAL DRAWING

INSTALLATION



Mounting / Installation may only be carried out by a qualified electrician!

DISPOSAL



SAFETY WARNINGS

Before initial operation, please make sure to follow all safety instructions that may be provided in the product information!