
AS-Interface gateway



Spec 2.1



90 7

Electrical connection

AS-Interface +

AS-Interface

Dimensions

Model number


VBG-CCL-G4F

CC Link Gateway IP65

Features


- · Gateway according to AS-Interface specification 2.1 for up to 62 units
- AS-Interface connection via flat cable • and EMS standard bottom section (included delivery)
- Degree of protection IP65 ٠
- Voltage supply from AS-Interface •
- PLC functionality •
- Error diagnostics via LEDs and LC • display

E G FG × H · · · ***** μP SLD \bigtriangledown DG



Terminating resistor (remove, unless last CC-IInk module)

Indicating / Operating means





Refer to "General Notes Relating to Pepperl+Fuchs Product Information" Pepperl+Fuchs Group

www.pepperl-fuchs.com

USA: +1 330 486 0001 fa-info@us.pepperl-fuchs.com

Germany: +49 621 776 4411 fa-info@de.pepperl-fuchs.com

Singapore: +65 6779 9091 fa-info@sg.pepperl-fuchs.com



1

AS-Interface gateway

VBG-CCL-G4F

Technical data

General specifications AS-Interface specification PLC-Functionality **Diagnostics** function

Indicators/operating means

Display LED SD LED RD LED AS-i ACTIVE LED CONFIG ERR LED PWR LED L RUN LED L ERR LED PRG ENABLE LED PRG MODE LED U AS-i Switch SET Button MODE

Electrical specifications Insulation voltage Rated operating voltage Rated operating current Interface Interface type Protocol Transfer rate Connection AS-Interface CC Link **Directive conformity** Electromagnetic compatibility Directive 2014/30/EU Standard conformity

Degree of protection AS-Interface Ambient conditions

Ambient temperature Storage temperature Mechanical specifications

Degree of protection Material

Housing

Mass

Construction type

V2.11 integrated integrated LED display, 2 digits, for addressing and error messages CC Link send data; LED green CC Link receive data; LED green AS-Interface operation normal; LED green configuration error; LED red voltage ON; LED green CC link in operation; LED green CC Link error; LED red autom. programming; LED green projecting mode active; LED yellow AS-Interface voltage; LED green Selection and setting of a slave address Mode selection/save configuration

> 500 V from AS-Interface

U

Ue

I_

≤ 200 mA from AS-Interface

remote device, 3 occupied stations according to CC-Link specification 156 kBit/s up to 10 MBit/s

cable piercing technology Cable gland M16 x 1.5 and cage spring terminals

EN 62026-2:2013

EN 60529:2000 EN 62026-2:2013

0 ... 55 °C (32 ... 131 °F) -25 ... 85 °C (-13 ... 185 °F)

IP65

PA 6 GF30 355 q Plastic housing with cable gland Function

The VBG-CCL-G4F is a complete CC-Link master for use in the field (IP65). The gateway's G4 field housing has the same advantages as the serial master in this design.

Two buttons are used for address assignment of the AS-Interface slaves and acceptance of the desired configuration. In configuration mode, all detected AS-Interface slaves are displayed on the 2-digit LCD. In normal operation, the LCD is blank unless the master detects a faulty AS-Interface slave. The LEDs, located on the front panel, show the current status of the AS-i line.

PLC Functionality

The VBG-CCL-G4F provides 16 kBytes of program memory, 8 kBytes of main memory, 1024 counters and 1024 timers for PLC functionality. These capacities suffice to process the data on the AS-Interface. Thus the master can also be operated in "stand-alone" mode. The program processing time is 2 ms per 1000 word commands. The programming language is based on the STEP5® programming language. The AS-Interface CTRL functions (upload, download, start, stop, read or write internal memory) are available in expanded mode

Accessories

U-G1P

AS-Interface module mounting base for connection to round cable (AS-Interface)

VAZ-G4-B Blind plug PG7

VAZ-G4-B1 Blind plug M12

Note

U-G1F base is included with delivery

> 122887_eng.xml Date of issue: 2018-01-29 Release date: 2018-01-29 15:05

Refer to "General Notes Relating to Pepperl+Fuchs Product Information" Pepperl+Fuchs Group w.pepperl-fuchs.com

Germany: +49 621 776 4411 fa-info@de.pepperl-fuchs.com



2