

90 Ð 8 114 ø4 (3x) Έ 100 112

Electrical connection

Model Number


IUT-F190-R4-V1-FR2-07

UHF readwrite station, Brazil

Features

- · Flexible UHF read/write station with medium detection range
- Ready-made PLC function blocks de-٠ signed for quick and easy system integration
- Compact and robust housing for • harsh industrial environments
- Switchable antenna polarization guar-٠ antees reliable tag detection and enhances process flow
- Multi-tag reading of up to 40 tags en-٠ sures increased productivity
- Connection via integrated RS-485 in-• terface





-	
В	
d	o not connect
S	hield

T

Technical data				
General specifications				
Operating frequency		915 MHz 928 MHz: Brazil Transmission licenses for other countries on request		
Emitted power		3 1250 mW EIRP adjustable		
Operating distance		typ. 2 m		
Indicators/operating means				
LED green		Power on		
LED yellow		Read/write operation successful		
LED blue		Transmission mode		
Electrical specifications				
Rated operating voltage	U _e	20 30 V DC , ripple 10 % _{SS}		
Current consumption		≤ 450 mA		
Power consumption	P ₀	≤9 W		
Surge protection		category 2		
Interface				
Physical		RS-485 point-to-point connection		
Protocol		ASCII		
Transfer rate		1200, 2400, 4800, 9600, 19200, 38400 (default) Bit/s		
Standard conformity				
Electromagnetic compatibility		EN 301489-1 V2.1.1:2017 EN 301489-3 V2.1.1:2017		
Degree of protection		EN 60529:2000		
Safety		EN 62368-1:2014+AC:2015		
Ambient conditions				
Classification		Environmental situation A (controlled environment)		
Ambient temperature		-20 70 °C (-4 158 °F) (Operation with nontransmission per ods, adjustable) -20 60 °C (-4 140 °F) (Continuous transmission mode)		
Storage temperature		-40 85 °C (-40 185 °F)		
Pollution degree		2		
Mechanical specifications				
Degree of protection		IP67		
Connection		M12 x 1 connector		
Material				
Housing		PA 6		
Base		diecast aluminum		
Mass		860 g		

Refer to "General Notes Relating to Pepperl+Fuchs Product Information" Pepperl+Fuchs Group www.pepperl-fuchs.com

USA: +1 330 486 0001 fa-info@us.pepperl-fuchs.com

Germany: +49 621 776 4411 fa-info@de.pepperl-fuchs.com

Singapore: +65 6779 9091 fa-info@sg.pepperl-fuchs.com



1

Notes

This product is a wireless device and may be operated only in the country for which a transmission license exists. Information regarding transmission licenses can be found on the datasheet for the product. If a product is released to a customer in a country for which there is no transmission license, the product may be operated only in the country for which a transmission license exists.

If a product does not correspond to the legal requirements in force in the EU but is released to a purchaser within the EU, the product is intended for use solely in the destination country of the end customer outside of the EU for which a transmission license exists. The product may therefore under no circumstances be used directly by the purchaser or released to third parties for the purpose of distribution, application or use on the market within the EU as part of a commercial activity.

In the event of an infringement, the purchaser is obliged to indemnify the supplier against any resulting damages, costs, penalty payments and other expenses.

Notes

Preferences:

Interface transfer rate: 38400 bps Port settings: 8 data bits, no parity, 1 stop bit, no handshake Transpondertype: 80

Function

The compact IUT-F190-R4-V1-FR2-07 read/write station operates in the UHF frequency range and is optimized for industrial use at medium distances. The device writes and reads passive transponders according to EPC Gen2 (ISO/IEC 18000-63). The read/write station can be used in Brazil. The read/write station is compliant with the relevant radio regulations.

Wide range of options supported for filtering data. The read/write station has an RS-485 interface and is connected via an M12 connector. The user can monitor the status of the read/write station using the integrated LEDs.

The read/write station has a typical detection range of approximately 2 m, which is determined by the transponder used and can be adjusted by the setting of the transmission power. Other influencing factors include the setup and installation of the specific application and the surrounding materials, in particular metal. The separately specified read and write distances for the respective transponders have been determined in a test laboratory under ideal conditions. For the actual read and write distances under real conditions, the combination of read/write station and transponder must be tested in the desired application.

Accessories

V1-G-5M-PUR-ABG-V1-W Connecting cable, M12 to M12, PUR cable 4-pin, shielded

V1-G-10M-PUR-ABG-V1-W

Connecting cable, M12 to M12, PUR cable 4-pin, shielded

IUC72-F152-M-FR1 Data carrier

IUC76-50-FR1 Data carrier

IUC76-F157-M-FR1 Data carrier

IUC76-F203-M-FR1 10pcs Data carrier

IUC77-F151-M-GBL Data carrier

IUC77-25L100-GBL 1000pcs Data carrier

IUC77-25L110-GBL 1000pcs Data carrier

IUZ-MH12 Mounting bracket for pole and wall mount- ରି

ng

IUZ-MH13 Mounting bracket for wall mounting

IUZ-MH15

Mounting aid for round steel ø 12 mm or sheet 1.5 mm ... 3 mm

Release date: 2018-02-09 11:07 Date of issue: 2018-02-13 309813_eng.xml

fa-info@us.pepperl-fuchs.com



www.pepperl-fuchs.com