Datasheet - BN 650-RZ

Magnetic reed switch / BN 650







- · With pre-wired cable
- Non-contact principle
- Long life
- Actuation from side
- · with bias magnet
- Construction form Ø 13 mm
- Thermoplastic enclosure
- Actuating distance up to 60 mm depending on actuating magnet and version
- · with central mounting

(Minor differences between the printed image and the original product may exist!)

Ordering details

 Product type description
 BN 650-RZ

 Article number
 101187283

 EAN Code
 4030661335681

 eCl@ss
 27-27-01-04

Approval

Approval

Global Properties

Permanent light

Standards

Compliance with the Directives (Y/N) C €

suitable for elevators (Y/N)

Mounting

Active principle

Materials

- Material of the housings
- Material of the cable mantle

Housing construction form

Weight

BN 650

-

Yes Yes

res

central with threated flange

Magnetic drive

Plastic, glass-fibre reinforced thermoplastic

LiYY

cylinder smooth

65

Recommended actuator

BP 10N, BP 10S, 2 x BP 10N, 2 x BP 10S, BP 15N, BP 15S, 2 x BP 15/2N, 2 x BP 15/2S, BP 34N, BP 34S, BP 20N, BP 20S, BP 31N, BP 31S, BP 11N, BP 11S, 2 x BP 11N, 2 x BP 11S, BP 12N, BP 12S, 2 x BP 12N, 2 x BP 12S, BP 21N, BP 21S, 2 x BP 21N, 2 x BP 21S, BE 20N, BE **20S**

BP 10, 2 x BP 10, 2 x BP 15/2, BP 15, 2 x BP 15, BP 34

- Lift switchgear

Mechanical data

Design of electrical connection

Cable length

Conductors

AWG-Number

Electrical lifetime

Switch distance

Mechanical life

Switching frequency Actuating planes

Active area

- notice

Type of actuation restistance to shock Resistance to vibration Bounce duration Latching (Y/N) bias magnet (Y/N)

Tightening torque for nuts

Actuating speed

Switching point accuracy

Cable

1

2 x 0,25

100.000.000 operations

1.000.000 ... 10.000.000 operations

300/

Actuation from side

lateral

15 ... 60

BP 10N = 15 mm

BP 10S = 15 mm

2 x BP 10N = 20 mm

2 x BP 10S = 20 mm

BP 15N = 17 mm

BP 15S = 17 mm

2 x BP 15/2N = 22 mm

2 x BP 15/2S = 22 mm

BP 34N = 10 ... 30 mm

BP 34S = 15 ... 30 mm

BP 20N = 25 mm BP 20S = 25 mm

BP 31N = 25 mm

BP 31S = 25 mm

BP 11N = 15 mm

BP 11S = 15 mm

2 x BP 11N = 25 mm 2 x BP 11S = 25 mm

BP 12N = 20 mm

BP 12S = 20 mm

2 x BP 12N = 10 ... 30 mm

2 x BP 12S = 10 ... 30 mm

BP 21N = 15 ... 45 mm

BP 21S = 15 ... 45 mm

2 x BP 21N = 20 ... 60 mm 2 x BP 21S = 20 ... 60 mm

BE 20N = 20 mm

BE 20S = 20 mm

Actuating distance up to 60 mm depending on actuating magnet and

version

The specifications with regard to the switching distances apply to the actuation of the individually mounted devices without ferromagnetic influence. Any change of the

distance, positive either negative, is possible due to ferromagnetic interference. When multiple actuating magnets are used, the mutual interference must be observed.

Magnet

30 / 11

10 ... 55 HZ, Amplitude 1 mm

0,15

Yes

Yes

18

± 0,25 mm

Ambient conditions

Ambient temperature

Min. environmental temperature
 Max. environmental temperature
 +70

Protection class IP67 to IEC/EN 60529

Electrical data

Design of control element	bistable contact
Number of snap-in contacts	1
Switching time - Close	0,35
Switching time - Open	30
Switch frequency	< 300
Dielectric strength	580
Switching voltage	200
Switching current	1 A
Switching capacity	30 /

Outputs

Design of control output

Design of control output Reed contakts

LED switching conditions display

LED switching conditions display (Y/N) No

ATEX

Explosion protection categories for gases

None
Explosion protected category for dusts

None

Dimensions

Dimensions of the sensor

- Length of sensor- Diameter of sensor13

notice

The opening and closing functions depend on the direction of actuation, the actuating magnets and the polarity of the actuating magnets.


When the switches and actuators come together, the colours must coincide: Red (S) to red (S) and green (N) to green (N).

This does not apply to the bistable contact.

Included in delivery

Actuators must be ordered separately.

Diagram



Note Diagram

opositive break NC contact

 $^{\scriptsize\textcircled{\scriptsize\textbf{1}}}_{\rm active}$

no active

____o Normally-open contact

o-t---o Normally-closed contact

Switch travel diagram



Notes Switch travel diagram

Contact closed

☐ Contact open

Setting range

(L) Break point

Positive opening sequence/- angle **VS** adjustable range of NO contact

VÖ adjustable range of NC contact

N after travel

Documents

Mounting and wiring instructions (de, en, fr) 99 kB, 11.07.2006

Code: m_bn6p01

Declaration of conformity (en) 186 kB, 12.07.2018

Code: __bn_p01_en

Declaration of conformity (de) 102 kB, 08.06.2016

Code: __bn_p01

notice - Switch distance (it) 27 kB, 12.04.2013

Code: s_bn_p01_it

notice - Switch distance (fr) 29 kB, 12.04.2013

Code: s_bn_p01_fr

notice - Switch distance (en) 27 kB, 12.04.2013

Code: s_bn_p01_en


notice - Switch distance (de) 28 kB, 12.04.2013

Code: s_bn_p01_de


notice - Switch distance (es) 28 kB, 12.04.2013

Code: s_bn_p01_es


Images




Dimensional drawing (basic component)



Switch travel diagram





Diagram

System components

Actuator



101057553 - BP 34

- thermoplastic enclosure
- · S-pole marked red
- N-pole marked green
- Suitable for mounting on ferrous material with a distance of 25 mm



101060163 - BP 15

- thermoplastic enclosure
- N-pole marked green
- S-pole marked red
- Suitable for mounting on ferrous material with a distance of 18 mm



101060165 - BP 15/2

- Unenclosed
- Polarity stamped in
- Suitable for mounting on ferrous material with a distance of 18 mm



101057531 - BP 10

- Unenclosed
- Colour coding of poles by lables

K.A. Schmersal GmbH & Co. KG, Möddinghofe 30, D-42279 Wuppertal The data and values have been checked throroughly. Technical modifications and errors excepted. Generiert am 13.02.2019 - 13:12:30h Kasbase 3.3.0.F.64I