

#### VK003029

#### **CONNECTION TECHNOLOGY • CABLE SOCKETS FIELD-ATTACHABLE**

ipf cable sockets are used primarily for establishing the electrical connection of sensors. Their features are characterized by rugged design, the highest protection classes (IP67 | IP68 | IP69K) and, if desired, with 360° shielding. With the features: bus-ready, suitable for use with drag chains and robots, resistance to oil and chemicals, resistance to welding sparks, their resistance to cleaning agents or high-pressure and steam-jet cleaning, the expanded temperature range of up to +230°C, the rapid interconnection technology and special data transmission properties, the cable sockets meet all requirements in automation technology.



# **MECHANICAL DATA**

| Contact body material                           | CuZn         |
|---|--------------|
| Contact coating material                        | Au           |
| Degree of protection (IP)                       | IP67         |
| Housing material                                | PBT          |
| Number of wires                                 | 5            |
| Perm. ambient temperature of cable, fixed cable | -25 °C 90 °C |
| Positioning of cable feed, housing side         | Straight     |
| Wire cross section                              | 0.75 mm²     |

## **ELECTRICAL DATA**


| Number of pins                              | 5           |
|---|-------------|
| Rated current In                            | 4 A         |
| Rated voltage                               | 60 V        |
| Shielded                                    | No          |
| Suitable for self-assembly                  | Yes         |
| Type of electrical connection, housing side | M12         |
| Type of plug-in contact, housing side       | Male (plug) |
| With LED display                            | No          |

## **OTHER DATA**

| Flame resistant | No |
|-----------------|----|
| Halogen-free    | No |
| IR-networked    | No |



#### **CONNECTION**



## **DIMENSIONAL DRAWING**







## **INSTALLATION**



Mounting / Installation may only be carried out by a qualified electrician!

# **DISPOSAL**



# **SAFETY WARNINGS**

Before initial operation, please make sure to follow all safety instructions that may be provided in the product information!